

.REM _

IDENTIFICATION

PRODUCT CODE: AC-E661D-MC
PRODUCT NAME: CXXYADO XY11 PLOT MOD
PRODUCT DATE: SEPTEMBER 1978
MAINTAINER: DEC/X11 SUPPORT GROUP

THE INFORMATION IN THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE AND SHOULD NOT BE CONSTRUED AS A COMMITMENT BY DIGITAL EQUIPMENT CORPORATION. DIGITAL EQUIPMENT CORPORATION ASSUMES NO RESPONSIBILITY FOR ANY ERRORS THAT MAY APPEAR IN THIS MANUAL.

THE SOFTWARE DESCRIBED IN THIS DOCUMENT IS FURNISHED TO THE PURCHASER UNDER A LICENSE FOR USE ON A SINGLE COMPUTER SYSTEM AND CAN BE COPIED (WITH INCLUSION OF DIGITALS COPYRIGHT NOTICE) ONLY FOR USE IN SUCH SYSTEM, EXCEPT AS MAY OTHERWISE BE PROVIDED IN WRITING BY DIGITAL.

DIGITAL EQUIPMENT CORPORATION ASSUMES NO RESPONSIBILITY FOR THE USE OR RELIABILITY OF ITS SOFTWARE ON EQUIPMENT THAT IS NOT SUPPLIED BY DIGITAL.

COPYRIGHT (C) 1973,1978 DIGITAL EQUIPMENT CORPORATION

1. ABSTRACT:

XYA IS AN IOMOD THAT EXERCISES THE XY11 PLOTTER INTERFACE.
A SQUARE WITH CROSSED CENTER LINES IS CONTINUOUSLY DRAWN
AS THE PAPER ROLL ADVANCES.

2. REQUIREMENTS:

HARDWARE: XY11 INTERFACE WITH ITS ASSOCIATED PLOTTER.

STORAGE:: XYA REQUIRES:

1. DECIMAL WORDS: 364
2. OCTAL WORDS: 0554
3. OCTAL BYTES: 1330

3. PASS DEFINITION:

EACH COMPLETE FIGURE CONSTITUTES A PASS OF XYA.

4. EXECUTION TIME:

XYA RUNNING ALONE ON A PDP11/05 PROCESSOR TAKES
APPROXIMATELY---MINUTES TO COMPLETE ONE PASS.

5. CONFIGURATION REQUIREMENTS:

DEFAULT PARAMETERS:

DEVADR: 172554, VECTOR: 120, BR1: 5

REQUIRED PARAMETERS:

NONE

6. DEVICE/OPTION SETUP:

- A. TURN PLOTTER POWER AND DRUM DRIVE ON.
- B. MANUALLY POSITION THE PEN TO THE LEFT MARGIN.

7. MODULE OPERATION:

- A. SETUP THE XY11 REGISTER ADDRESSES
- B. RAISE THE PEN AND FIND THE LEFT MARGIN.
- C. DRAW A SQUARE.
- D. DRAW A CROSS WITHIN THE SQUARE
- E. SPACE UP THE PAPER A DISTANCE ONE HALF THE SQUARE SIZE.
- F. REPEAT FROM 7.B

8. OPERATION OPTIONS:

MODULE LOCATION STEPS (XYA 1154) MAY BE USED TO CHANGE THE SIZE OF THE FIGURE.

9. NON-STANDARD PRINTOUTS:

NONE

```
000000- IOMOD <XYAD > 172554,120,5,10,23  
000000- MODULE 140000,XYAD,172554,120,5,10,23  
; TITLE XYAD DEC/X11 SYSTEM EXERCISER MODULE  
DDACOM VERSION 6 23-MAV-78  
;*****LIST BIN*****  
000000- BEGIN:  
000000- 054530 042101 040 MODNAM: .ASCII /XYAD / ;MODULE NAME  
000000- 000 XFLAG: .BYTE OPEN ;USED TO KEEP TRACK OF WBUFF USAGE  
000000- 172554 ADDR: 172554+0 ;1ST DEVICE ADDR.  
000010- 000120 VECTOR: 120+0 ;1ST DEVICE VECTOR.  
000012- 000 BR1: .BYTE PRIV5+0 ;1ST BR LEVEL-  
000013- 000 BR2: .BYTE PRIV+0 ;2ND BR LEVEL-  
000014- 000000 DIVI1: +1 ;DEVICE INDICATOR 1.  
000016- 000000 SR1: OPEN ;SWITCH REGISTER 1  
000020- 000000 SR2: OPEN ;SWITCH REGISTER 2  
000022- 000000 SR3: OPEN ;SWITCH REGISTER 3  
000024- 000000 SR4: OPEN ;SWITCH REGISTER 4  
;*****LIST BIN*****  
000026- 140000 STAT: 140000 ;STATUS WORD  
000030- 000224 INIT: START ;MODULE START ADDR.  
000032- 000224 SPOINT: MODSP ;MODULE STACK POINTER.  
000034- 000000 PASCNT: 0 ;PASS COUNTER.  
000036- 000012 ICNT: 10. ;# OF ITERATIONS PER PASS=10.  
000040- 000000 ICOUNT: 0 ;LOC TO COUNT ITERATIONS  
000042- 000000 SDFCNT: 0 ;LOC TO SAVE TOTAL SOFT ERRORS  
000044- 000000 HRDCHT: 0 ;LOC TO SAVE TOTAL HARD ERRORS  
000046- 000000 SDFPAS: 0 ;LOC TO SAVE SOFT ERRORS PER PASS  
000050- 000000 HRDPAS: 0 ;LOC TO SAVE HARD ERRORS PER PASS  
000052- 000000 SYSCNT: 0 ;# OF SVS ERRORS ACCUMULATED  
000054- 000000 RANNUM: 0 ;HOLDS RANDOM # WHEN RAND MACRO IS CALLED  
000056- 000000 CONFIG: 0  
000058- 000000 RES1: 0 ;RESERVED FOR MONITOR USE  
000060- 000000 RES2: 0 ;RESERVED FOR MONITOR USE  
000062- 000000 SVR0: OPEN ;LOC TO SAVE R0.  
000064- 000000 SVR1: OPEN ;LOC TO SAVE R1.  
000066- 000000 SVR2: OPEN ;LOC TO SAVE R2.  
000070- 000000 SVR3: OPEN ;LOC TO SAVE R3.  
000072- 000000 SVR4: OPEN ;LOC TO SAVE R4.  
000074- 000000 SVR5: OPEN ;LOC TO SAVE R5.  
000076- 000000 SVR6: OPEN ;LOC TO SAVE R6.  
000100- 000000 CSRA: OPEN ;ADDR OF CURRENT CSR.  
000102- 000000 SADR: OPEN ;ADDR OF GOOD DATA, OR  
000104- 000000 ACSR: OPEN ;CONTENTS OF CSR.  
000106- 000000 WASADR: OPEN ;ADDR OF BAD DATA, OR  
000108- 000000 ASAT: OPEN ;STATUS REG CONTENTS.  
000110- 000000 ERRTP: OPEN ;TYPE OF ERROR  
000112- 000000 ASB: OPEN ;EXPECTED DATA.  
000114- 000232 AMAS: OPEN ;ACTUAL DATA.  
000116- 000000 RSTRT: RSTRT ;RESTART ADDRESS AFTER END OF PASS  
000118- 000000 WDTG: OPEN ;WORDS TO MEMORY PER ITERATION  
000120- 000000 WDR: OPEN ;WCRTS FROM MEMORY PER ITERATION  
000122- 000023 INTR: OPEN ;# OF INTERRUPTS PER ITERATION  
IDNUM: 23 ;MODULE IDENTIFICATION NUMBER=23  
;*****LIST SPSIZ *****  
;MODULE STACK STARTS HERE.
```

```
000224- .WORD 0  
;*****LIST ENDR *****  
MODSP: *****  
;*****LIST ENDR *****
```

```
175 000224 012767 000030 177666 START: MOV #24,INTR ;24 INTERRUPTS/ITERATION
176 000232 016767 177550 001064 RESTR: MOV ADDR,XYCS ;LOAD XY11 CSR ADDRESS
177 000240 016767 177542 001060 MOV ADDR,XYDB ;LOAD XY11 DBR ADDRESS
178 000248 016767 000002 001052 ADD #2,XYDB
179 000256 016700 177530 MOV VECTOR,RO ;SETUP TO LOAD XY11 PI INFO
180 000260 012720 000306 MOV #STP1,@VECTOR ;LOAD PI VECTOR
181 000264 016720 177522 MOV BR1,(RO) ;LOAD BR LEVEL
182 000270 012777 000100 001026 MOV #16,(RO) ;ENABLE
183 000276 005077 001024 CLR @XYDB ;RAISE DUMMY INTERRUPT
184 000302 104400 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
185
186 000306 STP1: ;-----
187 ;PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
188 000306 000004 000000 000314 1$: MOV #STP2,@VECTOR ;CHANGE PI VECTOR
189 000314 012777 000342 177466 BEQ STP2,COUNT ;SET COUNTER
190 000322 012767 000625 000772 MOV #40,@XYDB ;PEN UP
191 000330 012777 000040 000770 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
192
193 000336 104400 000000
194
195 000342 STP2: ;-----
196 ;PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
197 000342 000004 000000 000350 1$: MOV #STP2A,@VECTOR ;CHANGE PI VECTOR
198 000350 012777 000370 177432 BEQ STP2A,COUNT ;PEN RIGHT
199 000356 012777 000010 000742 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
200
201 000364 104400 000000
202
203 000370 STP2A: ;-----
204 ;PIRQS,BEGIN,2$ ; QUEUE UP TO CONTINUE AT 2$ AND RTI
205 000370 000004 000000 000376 2$: DEC COUNT ;DONE?
206 000376 005367 000720 BEQ STP3 ;SKIP IF YES
207 000402 001405 000000 000714 MOV #10,@XYDB ;NO- PEN RIGHT
208 000404 012777 000010 000714 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
209
210 000412 104400 000000
211
212 000416 012777 000436 177364 STP3: MOV #STP4,@VECTOR ;CHANGE PI VECTOR
213 000424 012777 000620 000674 MOV #20,@XYDB ;PEN DOWN
214 000432 104400 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
215
216 000436 STP4: ;-----
217 ;PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
218 000436 000004 000000 000444 1$: MOV #STP5,@VECTOR ;CHANGE PI VECTOR
219 000444 012777 000472 177336 BEQ STP5,COUNT ;LOAD COUNT
220 000452 016767 000640 000642 MOV #10,@XYDB ;PEN RIGHT
221 000460 012777 000010 000640 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
222
223 000466 104400 000000
224
```

```
225 000472 STP5: ;-----
226 ;PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
227 000472 000004 000000 000500 1$: DEC COUNT ;DONE?
228 000500 005367 000616 BEQ STP6 ;SKIP IF YES
229 000504 001405 000010 000612 MOV #10,@XYDB ;NO- PEN RIGHT
230 000506 012777 000000 000612 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
231
232 000514 104400 000000
233
234 000520 012777 000546 177262 STP6: MOV #STP7,@VECTOR ;CHANGE PI VECTOR
235 000526 016767 000564 000566 MOV STP7,COUNT ;LOAD COUNT
236 000534 012777 000001 000564 MOV #1,@XYDB ;DROM DOWN
237 000542 104400 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
238
239 000546 STP7: ;-----
240 ;PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
241 000546 000004 000000 000554 1$: DEC COUNT ;DONE?
242 000554 005367 000542 BEQ STP10 ;YES- SKIP
243 000560 001405 000001 000536 MOV #1,@XYDB ;NO- DROM DOWN
244 000562 012777 000000 000536 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
245
246 000570 104400 000000
247
248 000574 012777 000622 177206 STP10: MOV #STP11,@VECTOR ;CHANGE PI VECTOR
249 000602 016767 000510 000512 MOV STP11,COUNT ;LOAD COUNTER
250 000610 012777 000004 000510 MOV #4,@XYDB ;PEN LEFT
251 000616 104400 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
252
253 000622 STP11: ;-----
254 ;PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
255 000622 000004 000000 000630 1$: DEC COUNT ;DONE?
256 000630 005367 000466 BEQ STP12 ;SKIP IF YES
257 000634 001405 000004 000462 MOV #4,@XYDB ;NO- PEN LEFT
258 000636 012777 000000 000462 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
259
260 000644 104400 000000
261
262 000650 012777 000676 177132 STP12: MOV #STP13,@VECTOR ;CHANGE PI VECTOR
263 000656 016767 000434 000436 MOV STP13,COUNT ;LOAD COUNTER
264 000664 012777 000002 000434 MOV #2,@XYDB ;DROM UP
265 000672 104400 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
266
267 000676 STP13: ;-----
268 ;PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
269 000676 000004 000000 000704 1$: DEC COUNT ;DONE?
270 000704 005367 000412 BEQ STP14 ;SKIP IF YES
271 000710 001405 000002 000406 MOV #2,@XYDB ;NO- DROM UP
272 000716 012777 000000 000406 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
273
274 000720 104400 000000
275
```

```
276 000724 012777 000752 177056 STP14: MOV #STP15,@VECTOR ;CHANGE PI VECTOR
277 000732 016767 000360 000360 MOV STEPS,COUNT ;LOAD COUNT
278 000740 012777 000011 000360 MOV #1,@XYDB ;DRUM DOWN AND PEN RIGHT
279 000746 104400 000000 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
280
281 000752 STP15:
282 -----
283 PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
284 -----
285 000760 005367 000336 1$: DEC COUNT ;DONE?
286 000764 001405 BEQ STP16 ;SKIP IF YES
287 000766 012777 000011 000332 MOV #1,@XYDB ;NO- DRUM DOWN AND PEN RIGHT
288 000774 104400 000000 000332 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
289
290 001000 012777 001020 177002 STP16: MOV #STP17,@VECTOR ;CHANGE PI VECTOR
291 001004 012777 000040 000312 MOV #40,@XYDB ;PEN UP
292 001014 104400 000000 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
293
294 001020 STP17:
295 -----
296 PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
297 -----
298 001024 012777 001054 176754 1$: MOV #STP20,@VECTOR ;CHANGE PI VECTOR
299 001028 012777 000256 000256 MOV STEPS,COUNT ;LOAD COUNTER
300 001032 012777 000000 000256 MOV #2,@XYDB ;DRUM UP
301 001050 104400 000000 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
302
303 001054 STP20:
304 -----
305 PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
306 -----
307 001062 005367 000234 1$: DEC COUNT ;DONE?
308 001066 001405 BEQ STP17 ;SKIP IF YES
309 001070 012777 000002 000230 MOV #2,@XYDB ;NO- DRUM UP
310 001076 104400 000000 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
311
312 001102 012777 001122 176700 STP21: MOV #STP22,@VECTOR ;CHANGE PI VECTOR
313 001110 012777 000020 000210 MOV #20,@XYDB ;PEN DOWN
314 001116 104400 000000 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
315
316 001122 STP22:
317 -----
318 PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
319 -----
320 001130 012777 001156 176652 1$: MOV #STP23,@VECTOR ;CHANGE PI VECTOR
321 001136 016767 000154 000156 MOV STEPS,COUNT ;LOAD COUNTER
322 001144 012777 000005 000154 MOV #5,@XYDB ;DRUM DOWN AND PEN LEFT
323 001152 104400 000000 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
324
```

```
325 001156 STP23:
326 -----
327 PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
328 -----
329 001164 000004 000000 001164 1$: DEC COUNT ;DONE?
330 001168 005367 000132 BEQ STP24 ;SKIP IF YES
331 001170 001405 000005 000126 MOV #5,@XYDB ;NO- DRUM DOWN AND PEN LEFT
332 001172 012777 000000 000126 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
333
334 001204 012777 001224 176576 STP24: MOV #STP25,@VECTOR ;CHANGE PI VECTOR
335 001212 012777 000040 000106 MOV #40,@XYDB ;PEN UP
336 001220 104400 000000 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
337
338 001224 STP25:
339 -----
340 PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
341 -----
342 001232 012777 001260 176550 1$: MOV #STP26,@VECTOR ;CHANGE PI VECTOR
343 001240 016767 000054 000054 MOV HALF,COUNT ;LOAD COUNTER
344 001246 012777 000001 000052 MOV #1,@XYDB ;DRUM DOWN
345 001254 104400 000000 000052 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
346
347 001260 STP26:
348 -----
349 PIRQS,BEGIN,1$ ; QUEUE UP TO CONTINUE AT 1$ AND RTI
350 -----
351 001266 005367 000030 1$: DEC COUNT ;DONE?
352 001274 001405 BEQ STP27 ;YES- REDRAW PATTERN
353 001276 012777 000001 000024 MOV #1,@XYDB ;NO- DRUM DOWN
354 001302 104400 000000 000000 EXITS,BEGIN ;EXIT TO MONITOR. MODULE WAIT FOR INTERRUPT.
355
356 001306 STP27:
357 ENDIT$,BEGIN ;SIGNAL END OF ITERATION.
358 001306 104413 000000 ;MONITOR SHALL TEST END OF PASS
359 001312 000167 177100 JMP STP3 ;NO GO DO IT AGAIN.
360
361 STEPS: 300-
362 HALF: 150-
363 COUNT: 0
364 XCS: 0
365 XYDB: 0
366
367 .END ;THAT'S ALL FOLKS!
```

ACSR	000102R	157#																		
ADDR	000006R	173#	176	177																
ADD22=	001000	173#																		
ASB	000106R	176#																		
ASTAT	000104R	159#																		
AMAS	000110R	162#																		
BEGIN	000000R	162#																		
		174#	184	188	193	197	201	205	210	214	218	223	227	232	236	241	245	250	254	259
		175#	341	345	350	354	358	363	367	372	376	381	385	390	394	399	403	408	412	417
		176#	357																	
BTT0	= 000001	177#																		
BTT1	= 000002	177#																		
BTT10	= 002000	177#																		
BTT11	= 004000	177#																		
BTT12	= 010000	177#																		
BTT13	= 020000	177#																		
BTT14	= 040000	177#																		
BTT15	= 080000	177#																		
BTT16	= 000004	177#																		
BTT17	= 000010	177#																		
BTT18	= 000020	177#																		
BTT19	= 000040	177#																		
BTT20	= 000200	177#																		
BTT21	= 000400	177#																		
BTT22	= 001000	177#																		
BREAKS	= 104407	177#																		
BR1	= 000012R	177#	181																	
BR2	= 000013R	177#																		
BTODS	= 104421	177#																		
CDAYS	= 104422	177#																		
COUNT	= 000056R	177#																		
COUNT	= 001322R	197#	207*	221*	229*	235*	243*	249*	257*	263*	271*	277*	285*	299*						
		307#	321*	329*	343*	351*	363#													
CSRA	= 000100R	177#																		
DATCKS	= 104411	177#																		
DATERS	= 104404	177#																		
DVID1	= 000014R	177#																		
ENDIT	= 104410	177#	357																	
ERR	= 104419	177#																		
ERRTYP	= 000106R	160#																		
EXITS	= 104400	177#	184	193	201	210	214	223	232	237	246	251	260	265						
		178#	279	288	292	301	310	314	323	332	336	345	354							
GETPAS	= 104415	178#																		
GWBUF	= 104414	178#																		
HAL	= 001320R	343#	362#																	
HRDCNT	= 000044R	178#																		
HRDCNT	= 104405	178#																		
HRDPAS	= 000050R	143#																		
ICONT	= 000036R	137#																		
ICOUNT	= 000049R	138#																		
TOWN	= 001012R	139#																		
INIT	= 000030R	134#																		
INTR	= 000120R	166#	175*																	
MAD22	= 104423	178#																		
MODNAM	= 000000R	121#																		

MODSP	= 000224R	135	173#																	
MSCNS	= 104403	177#																		
MSCS	= 104401	177#																		
NULL	= 000000	177#																		
OPEN	= 000000	124#	128	129	130	131	148	149	150	151	152	153	154	155						
		175#	159	161	162	164	165	166	175#											
DTODS	= 104420	175#																		
PASCNT	= 000034R	146#	188	197	205	218	227	241	255	269	283	296	305	318						
PIRQS	= 000004	175#	340	349																
POPSP	= 005726	175#																		
POPSP2	= 022626	175#																		
PRTY0	= 000000	126#	175#																	
PRTY1	= 000040	177#																		
PRTY2	= 000100	177#																		
PRTY3	= 000140	177#																		
PRTY4	= 000200	177#																		
PRTY5	= 000240	177#																		
PRTY6	= 000300	177#																		
PRTY7	= 000340	177#																		
PSM	= 177776	177#																		
PUSH	= 005746	177#																		
PUSH2	= 024646	177#																		
RANDS	= 104417	177#																		
RANDS	= 000054R	144#																		
RESSTRT	= 000232R	163#	176#																	
RESS3	= 000056R	146#																		
RESS3	= 000060R	147#																		
RESSTRT	= 000112R	163#																		
SBADD	= 000104R	155#																		
SOPCNT	= 000042	139#																		
SOPFA2	= 104406	141#																		
SOPFA2	= 000048R	141#																		
SPOINT	= 000032R	139#																		
SPTS1	= 000040	128#	168																	
SRI1	= 000016R	128#																		

